

Programming the Datalogic QuickScan QD2430



Restore Custom Default Configuration



Enter/Exit Programming Mode

Restore Custom Default Configuration

The **Restore Custom Default Configuration** setting will erase all previous settings and return the scanner to its default out-of-the-box configuration

Default LINK settings



Scan Mode = Object Detection



Codabar = Enable



Codabar Start/Stop Character Transmission = Don't Transmit

To configure recommended LINK settings...

1. Aim the scanner at the **Enter/Exit Programming Mode** code and press the trigger to begin programming
2. Aim the scanner at each code and press the trigger
 - a. If you wish to scan UPCs, skip the "Disable UPC" section
 - b. If you wish to scan ISBNs, skip the "Disable ISBN" section
3. Aim the scanner at the **Enter/Exit Programming Mode** code and press the trigger to finish programming

Disable UPC



UPC-A = Disable



UPC-E = Disable

To change the volume...

1. Aim the scanner at the **Enter/Exit Programming Mode** code and press the trigger to begin programming
2. Aim the scanner at the desired code and press the trigger
3. Aim the scanner at the **Enter/Exit Programming Mode** code and press the trigger to finish programming

Disable ISBN



EAN 13 = Disable



EAN 8 = Disable



Good Read Beep Volume = Low



Good Read Beep Volume = High

